

Product	Rated Watts	Mains Voltage	I_ac amps	LINK Choke
				I_ac amps (1)
10g	125	120	1.10	N/A
10g	125	240	.55	N/A
20g	250	120	2.10	N/A
20g	250	240	1.05	N/A
30g	250	120	3.00	N/A
30g	250	240	2.30	N/A
50g	440	120	5.20	N/A
50g	440	240	3.50	N/A
60g	500	120	5.70	N/A
60g	500	240	4.30	N/A
70g	700	120	8.3	N/A
70g	700	240 1ph	5.75	N/A
120g	1000	240 1ph	8.20	4.40
120g	1000	240 3ph	4.80	2.50
140g	1400	240 1ph	10.2	N/A
150g	1200	240 1 ph (2)	9.60	5.20
150g	1200	240 3ph	4.80	3.00
300g	2400	240 3ph	9.60	6.00
450g	3600	240 3ph	N/R	9.20
QuadBlock (3)	2400	330 D.C.	N/R	6.00
L				

Notes:

- (1) Link choke is wired between the rectifier D.C. output and the input to the filter caps.
- (2) Single phase operation will shorten filter capacitor life. Avoid if possible.
- (3) QuadBlock AC current is measured at the mains to the rectifier.

General Notes:

- 1. When using a clamp on current meter, position the clamp away from any other wires or interference. Magnetic components including fans cause reading errors if close to the current clamp.
- 2. The higher currents without a link choke are due to the 0.6 power factor. Using a link choke improves the power factor to 0.95 and extends filter capacitor life.
- 3. Currents are average and will vary slightly from listed values. Use as a reference guide.

Values reflect normal running conditions, Not Maximums.